

NTNU
Norwegian University of
Science and Technology

TMA4115 - Calculus 3

Lecture 23, April 10

Toke Meier Carlsen
Norwegian University of Science and Technology

Spring 2013

Review of last week's lecture

NTNU
Norwegian University of
Science and Technology

Review of last week's lecture

Last week we introduce and studied

Review of last week's lecture

Last week we introduce and studied

- *eigenvectors*, *eigenvalues* and *eigenspaces* of square matrices,

Review of last week's lecture

Last week we introduce and studied

- *eigenvectors*, *eigenvalues* and *eigenspaces* of square matrices,
- the *characteristic polynomial* of a square matrix,

Review of last week's lecture

Last week we introduce and studied

- *eigenvectors*, *eigenvalues* and *eigenspaces* of square matrices,
- the *characteristic polynomial* of a square matrix,
- *diagonal* matrices,

Review of last week's lecture

Last week we introduce and studied

- *eigenvectors*, *eigenvalues* and *eigenspaces* of square matrices,
- the *characteristic polynomial* of a square matrix,
- *diagonal* matrices,
- how to *diagonalizable* a matrix.

NTNU
Norwegian University of
Science and Technology

Today's lecture

Today's lecture

Today we shall study

NTNU
Norwegian University of
Science and Technology

Today's lecture

Today we shall study

- real matrices with complex eigenvalues,

NTNU
Norwegian University of
Science and Technology

Today's lecture

Today we shall study

- real matrices with complex eigenvalues,
- systems of first order differential equations.

NTNU
Norwegian University of
Science and Technology

Eigenvalues and eigenvectors

NTNU
Norwegian University of
Science and Technology

Eigenvalues and eigenvectors

Let A be an $n \times n$ matrix.

Eigenvalues and eigenvectors

Let A be an $n \times n$ matrix. Recall that:

- A scalar λ is an eigenvalue of A if and only if λ is a zero of the characteristic polynomial $\det(A - \lambda I_n)$ of A.

Eigenvalues and eigenvectors

Let A be an $n \times n$ matrix. Recall that:

- A scalar λ is an eigenvalue of A if and only if λ is a zero of the characteristic polynomial $\det(A - \lambda I_n)$ of A.
- If λ is an eigenvalue of A, then an eigenvector of A corresponding to λ is a nontrivial solution to the equation $A\mathbf{x} = \lambda\mathbf{x}$.

NTNU
Norwegian University of
Science and Technology

Complex eigenvalues and eigenvectors

NTNU
Norwegian University of
Science and Technology

Complex eigenvalues and eigenvectors

- A real matrix A might have a complex eigenvalue λ in which case the corresponding eigenvectors are also complex.

Complex eigenvalues and eigenvectors

- A real matrix A might have a complex eigenvalue λ in which case the corresponding eigenvectors are also complex.
- If λ is an eigenvalue of A with corresponding eigenvector $\mathbf{v}$, then $\overline{\lambda}$ is an eigenvalue of A with corresponding eigenvector $\overline{\mathbf{v}}$.

NTNU
Norwegian University of
Science and Technology

Example

NTNU
Norwegian University of
Science and Technology

Example

Let $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$.

Example

Let $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$. Then

$$\det(A - \lambda I_2) = \begin{vmatrix} 4-\lambda & -2 \\ 1 & 6-\lambda \end{vmatrix} = (4-\lambda)(6-\lambda)+2 = \lambda^2 - 10\lambda + 26$$

Example

Let $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$. Then

$$\det(A - \lambda I_2) = \begin{vmatrix} 4-\lambda & -2 \\ 1 & 6-\lambda \end{vmatrix} = (4-\lambda)(6-\lambda)+2 = \lambda^2 - 10\lambda + 26$$

and since the zeros of $\lambda^2 - 10\lambda + 26$ are

$$\lambda = \frac{10 \pm \sqrt{10^2 - 4 \cdot 26}}{2} = \frac{10 \pm \sqrt{-4}}{2} = \frac{10 \pm 2i}{2} = 5 \pm i,$$

NTNU
Norwegian University of
Science and Technology

Example

Let $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$. Then

$$\det(A - \lambda I_2) = \begin{vmatrix} 4-\lambda & -2 \\ 1 & 6-\lambda \end{vmatrix} = (4-\lambda)(6-\lambda)+2 = \lambda^2 - 10\lambda + 26$$

and since the zeros of $\lambda^2 - 10\lambda + 26$ are $\lambda = \frac{10 \pm \sqrt{10^2 - 4 \cdot 26}}{2} = \frac{10 \pm \sqrt{-4}}{2} = \frac{10 \pm 2i}{2} = 5 \pm i$, it follows that the eigenvalues of A are $5 \pm i$.

Example (cont.)

$$A-(5+i)I_2=\begin{bmatrix}4-(5+i) & -2\\ 1 & 6-(5+i)\end{bmatrix}=\begin{bmatrix}-1-i & -2\\ 1 & 1-i\end{bmatrix},$$

Example (cont.)

$$A-(5+i)I_2=\begin{bmatrix}4-(5+i) & -2\\ 1 & 6-(5+i)\end{bmatrix}=\begin{bmatrix}-1-i & -2\\ 1 & 1-i\end{bmatrix},$$

so $\mathbf{v}_1=\begin{bmatrix}1-i\\ -1\end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_1=5+i$.

Example (cont.)

$$A-(5+i)I_2=\begin{bmatrix}4-(5+i) & -2\\ 1 & 6-(5+i)\end{bmatrix}=\begin{bmatrix}-1-i & -2\\ 1 & 1-i\end{bmatrix},$$

so $\mathbf{v}_1=\begin{bmatrix}1-i\\ -1\end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_1=5+i$.

It follows that $\mathbf{v}_2=\begin{bmatrix}1+i\\ -1\end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_2=5-i$.

NTNU
Norwegian University of
Science and Technology

Example

NTNU
Norwegian University of
Science and Technology

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0.

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0. Then

$$\det(C - \lambda I_2) = \begin{vmatrix} a-\lambda & -b \\ b & a-\lambda \end{vmatrix} = (a-\lambda)^2 + b^2 = \lambda^2 - 2a\lambda + a^2 + b^2,$$

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0. Then

$$\det(C - \lambda I_2) = \begin{vmatrix} a-\lambda & -b \\ b & a-\lambda \end{vmatrix} = (a-\lambda)^2 + b^2 = \lambda^2 - 2a\lambda + a^2 + b^2,$$

and since the zeros of $\lambda^2 - 2a\lambda + a^2 + b^2$ are

$$\lambda = \frac{2a \pm \sqrt{4a^2 - (a^2+b^2)}}{2} = \frac{2a \pm \sqrt{-b^2}}{2} = \frac{2a \pm 2bi}{2} = a \pm bi,$$

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0. Then

$$\det(C - \lambda I_2) = \begin{vmatrix} a-\lambda & -b \\ b & a-\lambda \end{vmatrix} = (a-\lambda)^2 + b^2 = \lambda^2 - 2a\lambda + a^2 + b^2,$$

and since the zeros of $\lambda^2 - 2a\lambda + a^2 + b^2$ are $\lambda = \frac{2a \pm \sqrt{4a^2 - (a^2+b^2)}}{2} = \frac{2a \pm \sqrt{-b^2}}{2} = \frac{2a \pm 2bi}{2} = a \pm bi$, it follows that the eigenvalues of C are $a \pm bi$.

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0. Then

$$\det(C - \lambda I_2) = \begin{vmatrix} a-\lambda & -b \\ b & a-\lambda \end{vmatrix} = (a-\lambda)^2 + b^2 = \lambda^2 - 2a\lambda + a^2 + b^2,$$

and since the zeros of $\lambda^2 - 2a\lambda + a^2 + b^2$ are $\lambda = \frac{2a \pm \sqrt{4a^2 - (a^2+b^2)}}{2} = \frac{2a \pm \sqrt{-b^2}}{2} = \frac{2a \pm 2bi}{2} = a \pm bi$, it follows that the eigenvalues of C are $a \pm bi$.

Let $r = |a + bi| = \sqrt{a^2 + b^2}$ and $\theta = \text{Arg}\,(a + bi)$.

NTNU
Norwegian University of
Science and Technology

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0. Then

$$\det(C - \lambda I_2) = \begin{vmatrix} a-\lambda & -b \\ b & a-\lambda \end{vmatrix} = (a-\lambda)^2 + b^2 = \lambda^2 - 2a\lambda + a^2 + b^2,$$

and since the zeros of $\lambda^2 - 2a\lambda + a^2 + b^2$ are $\lambda = \frac{2a \pm \sqrt{4a^2 - (a^2+b^2)}}{2} = \frac{2a \pm \sqrt{-b^2}}{2} = \frac{2a \pm 2bi}{2} = a \pm bi$, it follows that the eigenvalues of C are $a \pm bi$.
Let $r = |a + bi| = \sqrt{a^2 + b^2}$ and $\theta = \operatorname{Arg}(a + bi)$. Then $a = r\cos\theta$ and $b = r\sin\theta$,

NTNU
Norwegian University of
Science and Technology

Example

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers not both equal to 0. Then

$$\det(C - \lambda I_2) = \begin{vmatrix} a-\lambda & -b \\ b & a-\lambda \end{vmatrix} = (a-\lambda)^2 + b^2 = \lambda^2 - 2a\lambda + a^2 + b^2,$$

and since the zeros of $\lambda^2 - 2a\lambda + a^2 + b^2$ are $\lambda = \frac{2a \pm \sqrt{4a^2 - (a^2+b^2)}}{2} = \frac{2a \pm \sqrt{-b^2}}{2} = \frac{2a \pm 2bi}{2} = a \pm bi$, it follows that the eigenvalues of C are $a \pm bi$.

Let $r = |a + bi| = \sqrt{a^2 + b^2}$ and $\theta = \operatorname{Arg}(a + bi)$. Then $a = r\cos\theta$ and $b = r\sin\theta$, so

$$\begin{bmatrix} r & 0 \\ 0 & r \end{bmatrix} \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix} = \begin{bmatrix} a & -b \\ b & a \end{bmatrix} = C.$$

NTNU
Norwegian University of
Science and Technology

Example (cont.)

It follows that the linear transformation $\mathbf{x} \mapsto C\mathbf{x}$ may be viewed as the composition of a rotation by $\operatorname{Arg}(a+bi)$ followed by a scaling by $|a+bi|$.

Rotation and scaling in $\mathbb{R}^2$

NTNU
Norwegian University of
Science and Technology

Rotation and scaling in $\mathbb{R}^2$

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers which are not both zero, and let $r = |a + ib| = \sqrt{a^2 + b^2}$ and $\theta = \text{Arg}(a + ib)$.

Rotation and scaling in $\mathbb{R}^2$

Let $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$ where a and b are real numbers which are not both zero, and let $r = |a + ib| = \sqrt{a^2 + b^2}$ and $\theta = \text{Arg}(a + ib)$.

Then $C = \begin{bmatrix} r & 0 \\ 0 & r \end{bmatrix} \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix}$ and the transformation $\mathbf{x} \mapsto C\mathbf{x}$ may be viewed as the composition of a rotation by $\text{Arg}\,(a + bi)$ followed by a scaling by $|a + bi|$.

Example

Example

Let us return to the example where $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$.

Example

Let us return to the example where $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$. We have seen that the eigenvalues of A are $5 \pm i$, and that $\mathbf{v}_1 = \begin{bmatrix} 1-i \\ -1 \end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_1 = 5 + i$, and that $\mathbf{v}_2 = \begin{bmatrix} 1+i \\ -1 \end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_2 = 5 - i$.

Example

Let us return to the example where $A = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix}$. We have seen that the eigenvalues of A are $5 \pm i$, and that $\mathbf{v}_1 = \begin{bmatrix} 1-i \\ -1 \end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_1 = 5 + i$, and that $\mathbf{v}_2 = \begin{bmatrix} 1+i \\ -1 \end{bmatrix}$ is an eigenvalue of A corresponding to the eigenvalue $\lambda_2 = 5 - i$.

Let $P = [\mathrm{Re}(\mathbf{v}_1) \ \mathrm{Im}(\mathbf{v}_1)] = \begin{bmatrix} 1 & -1 \\ -1 & 0 \end{bmatrix}$ and

$$C = \begin{bmatrix} \mathrm{Re}(\lambda_1) & \mathrm{Im}(\lambda_1) \\ -\mathrm{Im}(\lambda_1) & \mathrm{Re}(\lambda_1) \end{bmatrix} = \begin{bmatrix} 5 & 1 \\ -1 & 5 \end{bmatrix}.$$

NTNU
Norwegian University of
Science and Technology

Example (cont.)

Then P is invertible, and

$$AP = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix} \begin{bmatrix} 1 & -1 \\ -1 & 0 \end{bmatrix} = \begin{bmatrix} 6 & -4 \\ -5 & -1 \end{bmatrix} \text{ and}$$

$$\begin{bmatrix} 1 & -1 \\ -1 & 0 \end{bmatrix} \begin{bmatrix} 5 & 1 \\ -1 & 5 \end{bmatrix} = \begin{bmatrix} 6 & -4 \\ -5 & -1 \end{bmatrix},$$

Example (cont.)

Then P is invertible, and

$$AP = \begin{bmatrix} 4 & -2 \\ 1 & 6 \end{bmatrix} \begin{bmatrix} 1 & -1 \\ -1 & 0 \end{bmatrix} = \begin{bmatrix} 6 & -4 \\ -5 & -1 \end{bmatrix} \text{ and}$$

$$\begin{bmatrix} 1 & -1 \\ -1 & 0 \end{bmatrix} \begin{bmatrix} 5 & 1 \\ -1 & 5 \end{bmatrix} = \begin{bmatrix} 6 & -4 \\ -5 & -1 \end{bmatrix}, \text{ so } A = PCP^{-1}.$$

Real 2×2 matrices with complex eigenvalues

Real 2×2 matrices with complex eigenvalues

Theorem 9

Let A be a real 2×2 matrix with a complex eigenvalue $\lambda = a - bi$ $(b \neq 0)$ and an associated eigenvector $\mathbf{v}$ in $\mathbb{C}^2$.

Real 2×2 matrices with complex eigenvalues

Theorem 9

Let A be a real 2×2 matrix with a complex eigenvalue $\lambda = a - bi$ $(b \neq 0)$ and an associated eigenvector $\mathbf{v}$ in $\mathbb{C}^2$. Then

$$A = PCP^{-1}$$

where $P = [\mathrm{Re}(\mathbf{v}) \ \ \mathrm{Im}(\mathbf{v})]$ and $C = \begin{bmatrix} a & -b \\ b & a \end{bmatrix}$.

NTNU
Norwegian University of
Science and Technology

Problem 6 from the exam from December 2011

Let $A = \begin{bmatrix} 1 & -\sqrt{3} \\ \sqrt{3} & 1 \end{bmatrix}$.

1. Show that $\mathbf{v} = \begin{bmatrix} 1 \\ i \end{bmatrix}$ is a (complex) eigenvector of A.
2. Find the complex eigenvalues and complex eigenvectors of A.

NTNU
Norwegian University of Science and Technology

Solution

NTNU
Norwegian University of
Science and Technology

Solution

$$A\mathbf{v} = \begin{bmatrix} 1 & -\sqrt{3} \\ \sqrt{3} & 1 \end{bmatrix} \begin{bmatrix} 1 \\ i \end{bmatrix} = \begin{bmatrix} 1 - \sqrt{3}i \\ \sqrt{3} - i \end{bmatrix}$$

$$= (1 - \sqrt{3}i) \begin{bmatrix} 1 \\ i \end{bmatrix} = (1 - \sqrt{3}i)\mathbf{v}$$

(because $(1 - \sqrt{3}i)i = i - \sqrt{3}i^2 = \sqrt{3} - i$),

Solution

$$A\mathbf{v} = \begin{bmatrix} 1 & -\sqrt{3} \\ \sqrt{3} & 1 \end{bmatrix} \begin{bmatrix} 1 \\ i \end{bmatrix} = \begin{bmatrix} 1 - \sqrt{3}i \\ \sqrt{3} - i \end{bmatrix}$$
$$= (1 - \sqrt{3}i) \begin{bmatrix} 1 \\ i \end{bmatrix} = (1 - \sqrt{3}i)\mathbf{v}$$

(because $(1 - \sqrt{3}i)i = i - \sqrt{3}i^2 = \sqrt{3} - i$), so $\mathbf{v}$ is an eigenvector of A with corresponding eigenvalue $(1 - \sqrt{3}i)$.

Solution

$$A\mathbf{v} = \begin{bmatrix} 1 & -\sqrt{3} \\ \sqrt{3} & 1 \end{bmatrix} \begin{bmatrix} 1 \\ i \end{bmatrix} = \begin{bmatrix} 1 - \sqrt{3}i \\ \sqrt{3} - i \end{bmatrix}$$
$$= (1 - \sqrt{3}i) \begin{bmatrix} 1 \\ i \end{bmatrix} = (1 - \sqrt{3}i)\mathbf{v}$$

(because $(1 - \sqrt{3}i)i = i - \sqrt{3}i^2 = \sqrt{3} - i$), so $\mathbf{v}$ is an eigenvector of A with corresponding eigenvalue $(1 - \sqrt{3}i)$.

It follows that $\bar{\mathbf{v}} = \begin{bmatrix} 1 \\ -i \end{bmatrix}$ is an eigenvector of A with corresponding eigenvalue $(1 + \sqrt{3}i)$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Since A is a 2×2 matrix, it cannot have more than 2 eigenvalues, and the multiplicity of $(1 - \sqrt{3}i)$ and $(1 + \sqrt{3}i)$ must be 1.

Solution (cont.)

Since A is a 2×2 matrix, it cannot have more than 2 eigenvalues, and the multiplicity of $(1 - \sqrt{3}i)$ and $(1 + \sqrt{3}i)$ must be 1.
It follows that the eigenvalues of A are $(1 - \sqrt{3}i)$ and $(1 + \sqrt{3}i)$ and that the eigenvectors of A are
$\left\{ t \begin{bmatrix} 1 \\ i \end{bmatrix} : t \in \mathbb{C},\ t \neq 0 \right\}$ and $\left\{ t \begin{bmatrix} 1 \\ -i \end{bmatrix} : t \in \mathbb{C},\ t \neq 0 \right\}$.

NTNU
Norwegian University of
Science and Technology

Systems of first order differential equations

NTNU
Norwegian University of
Science and Technology

Systems of first order differential equations

A *system of first order differential equations with constant coefficients* is a system of differential equations

$$\begin{aligned} x_1' &= a_{11}x_1 + \cdots + a_{1n}x_n \\ x_2' &= a_{21}x_1 + \cdots + a_{2n}x_n \\ &\vdots \\ x_n' &= a_{n1}x_1 + \cdots + a_{nn}x_n \end{aligned}$$

where $x_1, \ldots, x_n$ are differentiable functions of t with derivatives $x_1', \ldots, x_n'$, and the a_{ij} are constants.

NTNU
Norwegian University of Science and Technology

Example

NTNU
Norwegian University of
Science and Technology

Example

$$x_1'(t) = 5x_1(t) - x_2(t)$$
$$x_2'(t) = -x_1(t) + 5x_2(t)$$

is a system of first order differential equations with constant coefficients.

Systems of first order differential equations

If we let

$$\mathbf{x}(t) = \begin{bmatrix} x_1(t) \\ \vdots \\ x_n(t) \end{bmatrix} \quad \mathbf{x}'(t) = \begin{bmatrix} x_1'(t) \\ \vdots \\ x_n'(t) \end{bmatrix} \text{ and } A = \begin{bmatrix} a_{11} & \dots & a_{1n} \\ \vdots & & \vdots \\ a_{n1} & \dots & a_{nn} \end{bmatrix}$$

then we write the system as $\mathbf{x}'(t) = A\mathbf{x}(t)$.

NTNU
Norwegian University of
Science and Technology

Example

Example

The system

$$x_1'(t) = 5x_1(t) - x_2(t)$$
$$x_2'(t) = -x_1(t) + 5x_2(t)$$

can be written as $\mathbf{x}'(t) = A\mathbf{x}(t)$ where $\mathbf{x}(t) = \begin{bmatrix} x_1(t) \\ x_2(t) \end{bmatrix}$ and $A = \begin{bmatrix} 5 & -1 \\ -1 & 5 \end{bmatrix}$.

NTNU
Norwegian University of
Science and Technology

Systems of first order differential equations

- If $\mathbf{u}_1, \ldots, \mathbf{u}_k$ are solutions to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$, then any linear combination $c_1\mathbf{u}_1 + \cdots + c_k\mathbf{u}_k$ of $\mathbf{u}_1, \ldots, \mathbf{u}_k$ is also a solution to $\mathbf{x}'(t) = A\mathbf{x}(t)$.

NTNU
Norwegian University of
Science and Technology

Systems of first order differential equations

- If $\mathbf{u}_1, \ldots, \mathbf{u}_k$ are solutions to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$, then any linear combination $c_1\mathbf{u}_1 + \cdots + c_k\mathbf{u}_k$ of $\mathbf{u}_1, \ldots, \mathbf{u}_k$ is also a solution to $\mathbf{x}'(t) = A\mathbf{x}(t)$.
- The solution set of $\mathbf{x}'(t) = A\mathbf{x}(t)$ is an n-dimensional vector space, so if $\mathbf{v}_1, \ldots, \mathbf{v}_n$ are n linearly independent solutions to $\mathbf{x}'(t) = A\mathbf{x}(t)$, then any solution to $\mathbf{x}'(t) = A\mathbf{x}(t)$ is a linear combination of $\mathbf{v}_1, \ldots, \mathbf{v}_n$.

NTNU
Norwegian University of
Science and Technology

Example

Let us find the general solution to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ where $A = \begin{bmatrix} -1 & 0 \\ 0 & 4 \end{bmatrix}$.

NTNU
Norwegian University of
Science and Technology

Solution

NTNU
Norwegian University of
Science and Technology

Solution

The equation $\mathbf{x}'(t) = A\mathbf{x}(t)$ is equivalent to the system

$$x_1'(t) = -x_1(t)$$
$$x_2'(t) = 4x_2(t)$$

Solution

The equation $\mathbf{x}'(t) = A\mathbf{x}(t)$ is equivalent to the system

$$x_1'(t) = -x_1(t)$$
$$x_2'(t) = 4x_2(t)$$

The solution to that system is $x_1(t) = c_1 e^{-t}$ and $x_2(t) = c_2 e^{4t}$,

NTNU
Norwegian University of
Science and Technology

Solution

The equation $\mathbf{x}'(t) = A\mathbf{x}(t)$ is equivalent to the system

$$x_1'(t) = -x_1(t)$$
$$x_2'(t) = 4x_2(t)$$

The solution to that system is $x_1(t) = c_1 e^{-t}$ and $x_2(t) = c_2 e^{4t}$, so the general solution to $\mathbf{x}'(t) = A\mathbf{x}(t)$ is

$$\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 0 \end{bmatrix} e^{-t} + c_2 \begin{bmatrix} 0 \\ 1 \end{bmatrix} e^{4t}.$$

NTNU
Norwegian University of
Science and Technology

Attractors, repellers and saddle points

NTNU
Norwegian University of
Science and Technology

Attractors, repellers and saddle points

Let $\mathbf{x}'(t) = A\mathbf{x}(t)$ be a system of first order differential equations.

Attractors, repellers and saddle points

Let $\mathbf{x}'(t) = A\mathbf{x}(t)$ be a system of first order differential equations.

- The origin is called an *attractor* (or a *sink*) if every solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ converges to $\mathbf{0}$ as $t \to \infty$.

NTNU
Norwegian University of
Science and Technology

Attractors, repellers and saddle points

Let $\mathbf{x}'(t) = A\mathbf{x}(t)$ be a system of first order differential equations.

- The origin is called an *attractor* (or a *sink*) if every solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ converges to $\mathbf{0}$ as $t \to \infty$.
- The origin is called a *repeller* (or a *source*) if every solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ converges to $\mathbf{0}$ as $t \to -\infty$.

NTNU
Norwegian University of
Science and Technology

Attractors, repellers and saddle points

Let $\mathbf{x}'(t) = A\mathbf{x}(t)$ be a system of first order differential equations.

- The origin is called an *attractor* (or a *sink*) if every solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ converges to $\mathbf{0}$ as $t \to \infty$.
- The origin is called a *repeller* (or a *source*) if every solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ converges to $\mathbf{0}$ as $t \to -\infty$.
- The origin is called a *saddle point* if there is a solution $\mathbf{x}_1$ of $\mathbf{x}'(t) = A\mathbf{x}(t)$ that converges to $\mathbf{0}$ as $t \to \infty$ and a solution $\mathbf{x}_2$ of $\mathbf{x}'(t) = A\mathbf{x}(t)$ that converges to $\mathbf{0}$ as $t \to -\infty$.

NTNU
Norwegian University of Science and Technology

Example

Example

Let us return to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ where $A = \begin{bmatrix} -1 & 0 \\ 0 & 4 \end{bmatrix}$.

Example

Let us return to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ where $A = \begin{bmatrix} -1 & 0 \\ 0 & 4 \end{bmatrix}$.

We have seen that the general solution of the system is

$$\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 0 \end{bmatrix} e^{-t} + c_2 \begin{bmatrix} 0 \\ 1 \end{bmatrix} e^{4t}.$$

NTNU
Norwegian University of
Science and Technology

Example

Let us return to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ where $A = \begin{bmatrix} -1 & 0 \\ 0 & 4 \end{bmatrix}$.

We have seen that the general solution of the system is

$\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 0 \end{bmatrix} e^{-t} + c_2 \begin{bmatrix} 0 \\ 1 \end{bmatrix} e^{4t}$.

Since $\mathbf{x}_1(t) = \begin{bmatrix} 1 \\ 0 \end{bmatrix} e^{-t} \to \mathbf{0}$ as $t \to \infty$, and $\mathbf{x}_2(t) = \begin{bmatrix} 0 \\ 1 \end{bmatrix} e^{4t} \to \mathbf{0}$ as $t \to -\infty$,

NTNU
Norwegian University of
Science and Technology

Example

Let us return to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ where $A = \begin{bmatrix} -1 & 0 \\ 0 & 4 \end{bmatrix}$.

We have seen that the general solution of the system is

$\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 0 \end{bmatrix} e^{-t} + c_2 \begin{bmatrix} 0 \\ 1 \end{bmatrix} e^{4t}$.

Since $\mathbf{x}_1(t) = \begin{bmatrix} 1 \\ 0 \end{bmatrix} e^{-t} \to \mathbf{0}$ as $t \to \infty$, and $\mathbf{x}_2(t) = \begin{bmatrix} 0 \\ 1 \end{bmatrix} e^{4t} \to \mathbf{0}$ as $t \to -\infty$, the origin is a saddle point in this example.

NTNU
Norwegian University of
Science and Technology

Example

Let us find the general solution to the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ that satisfies $\mathbf{x}(0) = \begin{bmatrix} 2 \\ 4 \end{bmatrix}$, where $A = \begin{bmatrix} 5 & -1 \\ -1 & 5 \end{bmatrix}$, and determine if the origin is an attractor, repeller, or a saddle point.

NTNU
Norwegian University of
Science and Technology

Solution

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

$\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ is an eigenvector corresponding to 4.

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

$\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ is an eigenvector corresponding to 4.

$\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ is an eigenvector corresponding to 6.

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

$\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ is an eigenvector corresponding to 4.

$\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ is an eigenvector corresponding to 6.

Let $\mathbf{x}_1(t) = \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t}$ and $\mathbf{x}_2(t) = \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$.

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

$\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ is an eigenvector corresponding to 4.

$\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ is an eigenvector corresponding to 6.

Let $\mathbf{x}_1(t) = \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t}$ and $\mathbf{x}_2(t) = \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$. Then

$$A\mathbf{x}_1(t) = A \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} = 4 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} = \mathbf{x}_1'(t)$$

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

$\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ is an eigenvector corresponding to 4.

$\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ is an eigenvector corresponding to 6.

Let $\mathbf{x}_1(t) = \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t}$ and $\mathbf{x}_2(t) = \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$. Then

$$A\mathbf{x}_1(t) = A \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} = 4 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} = \mathbf{x}_1'(t) \text{ and}$$

$$A\mathbf{x}_2(t) = A \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t} = 6 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t} = \mathbf{x}_2'(t),$$

NTNU
Norwegian University of
Science and Technology

Solution

The eigenvalues of A are 4 and 6.

$\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ is an eigenvector corresponding to 4.

$\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ is an eigenvector corresponding to 6.

Let $\mathbf{x}_1(t) = \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t}$ and $\mathbf{x}_2(t) = \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$. Then

$A\mathbf{x}_1(t) = A \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} = 4 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} = \mathbf{x}_1'(t)$ and

$A\mathbf{x}_2(t) = A \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t} = 6 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t} = \mathbf{x}_2'(t)$, so $\mathbf{x}_1$ and $\mathbf{x}_2$ are solutions to $\mathbf{x}'(t) = A\mathbf{x}(t)$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$. By evaluating at $t = 0$ we get $c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \mathbf{0}$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$. By evaluating at $t = 0$ we get $c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \mathbf{0}$. Since $\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ and $\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ are linearly independent, it follows that $c_1 = c_2 = 0$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$. By evaluating at $t = 0$ we get $c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \mathbf{0}$. Since $\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ and $\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ are linearly independent, it follows that $c_1 = c_2 = 0$. This shows that $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$ are linearly independent.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$. By evaluating at $t = 0$ we get $c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \mathbf{0}$. Since $\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ and $\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ are linearly independent, it follows that $c_1 = c_2 = 0$. This shows that $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$ are linearly independent. It follows that $\{\mathbf{x}_1(t), \mathbf{x}_2(t)\}$ is a basis for the set of solutions of $\mathbf{x}'(t) = A\mathbf{x}(t)$, and thus that any solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ is a linear combination of $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$.
Let $\mathbf{x}(t) = c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t)$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$. By evaluating at $t = 0$ we get $c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \mathbf{0}$. Since $\begin{bmatrix} 1 \\ 1 \end{bmatrix}$ and $\begin{bmatrix} 1 \\ -1 \end{bmatrix}$ are linearly independent, it follows that $c_1 = c_2 = 0$. This shows that $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$ are linearly independent. It follows that $\{\mathbf{x}_1(t), \mathbf{x}_2(t)\}$ is a basis for the set of solutions of $\mathbf{x}'(t) = A\mathbf{x}(t)$, and thus that any solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ is a linear combination of $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$.

Let $\mathbf{x}(t) = c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t)$. Then

$$\mathbf{x}(0) = c_1\mathbf{x}_1(0) + c_2\mathbf{x}_2(0) = c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \begin{bmatrix} c_1 + c_2 \\ c_1 - c_2 \end{bmatrix},$$

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Suppose that $c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t) = \mathbf{0}$. By evaluating at $t = 0$ we get $c_1\begin{bmatrix}1\\1\end{bmatrix} + c_2\begin{bmatrix}1\\-1\end{bmatrix} = \mathbf{0}$. Since $\begin{bmatrix}1\\1\end{bmatrix}$ and $\begin{bmatrix}1\\-1\end{bmatrix}$ are linearly independent, it follows that $c_1 = c_2 = 0$. This shows that $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$ are linearly independent. It follows that $\{\mathbf{x}_1(t), \mathbf{x}_2(t)\}$ is a basis for the set of solutions of $\mathbf{x}'(t) = A\mathbf{x}(t)$, and thus that any solution of $\mathbf{x}'(t) = A\mathbf{x}(t)$ is a linear combination of $\mathbf{x}_1(t)$ and $\mathbf{x}_2(t)$.

Let $\mathbf{x}(t) = c_1\mathbf{x}_1(t) + c_2\mathbf{x}_2(t)$. Then

$$\mathbf{x}(0) = c_1\mathbf{x}_1(0) + c_2\mathbf{x}_2(0) = c_1\begin{bmatrix}1\\1\end{bmatrix} + c_2\begin{bmatrix}1\\-1\end{bmatrix} = \begin{bmatrix}c_1 + c_2\\c_1 - c_2\end{bmatrix}, \text{ so}$$

$\mathbf{x}(0) = \begin{bmatrix}2\\4\end{bmatrix}$ if and only if $c_1 + c_2 = 2$ and $c_1 - c_2 = 4$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

The solution to the system

$$c_1 + c_2 = 2$$
$$c_1 - c_2 = 4$$

is $c_1 = 3$, $c_2 = -1$,

Solution (cont.)

The solution to the system

$$c_1 + c_2 = 2$$
$$c_1 - c_2 = 4$$

is $c_1 = 3$, $c_2 = -1$, so

$\mathbf{x}(t) = 3\mathbf{x}_1(t) - \mathbf{x}_2(t) = 3\begin{bmatrix}1\\1\end{bmatrix}e^{4t} - \begin{bmatrix}1\\-1\end{bmatrix}e^{6t}$ is a solution to $\mathbf{x}'(t) = A\mathbf{x}(t)$ that satisfies $\mathbf{x}(0) = \begin{bmatrix}2\\4\end{bmatrix}$.

NTNU
Norwegian University of
Science and Technology

Solution (cont.)

Since the general solution of the system is

$$\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$$

Solution (cont.)

Since the general solution of the system is

$\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$ and

$c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t} \to \mathbf{0}$ as $t \to -\infty$ for all c_1 and c_2,

Solution (cont.)

Since the general solution of the system is $\mathbf{x}(t) = c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t}$ and $c_1 \begin{bmatrix} 1 \\ 1 \end{bmatrix} e^{4t} + c_2 \begin{bmatrix} 1 \\ -1 \end{bmatrix} e^{6t} \to \mathbf{0}$ as $t \to -\infty$ for all c_1 and c_2, we see that the origin is a repeller.

The general solution to a system of first order differential equations

NTNU
Norwegian University of
Science and Technology

The general solution to a system of first order differential equations

If an $n \times n$ matrix A has n linear independent eigenvectors $\mathbf{v}_1, \ldots, \mathbf{v}_n$ with corresponding eigenvalues $\lambda_1, \ldots, \lambda_n$, then the general solution of the system $\mathbf{x}'(t) = A\mathbf{x}(t)$ is

$$\mathbf{x}(t) = c_1\mathbf{v}_1 e^{\lambda_1 t} + \cdots + c_n\mathbf{v}_n e^{\lambda_n t}$$

where $c_1, \ldots, c_n$ are constants.

NTNU
Norwegian University of
Science and Technology

Tomorrow's lecture

Tomorrow we shall continue studying systems of first order differential equations. Section 5.7 in "Linear Algebras and Its Applications" (pages 295-301, and 311-319), and Section 4.2 in "Second-Order Equations" (pages xlv-xlix).

NTNU
Norwegian University of
Science and Technology